## SIEMENS

## Data sheet

## 6ES7131-6BF01-2AA0



SIMATIC ET 200SP, Digital input module, DI 8x 24V DC Basic, type 2 (IEC 61131), sink input, (PNP, P-reading), Packing unit: 10 pieces, fits to BU-type A0, Colour Code CC01, input delay time 0,05..20ms, module diagnostics for: supply voltage

General information	
Product type designation	DI 8x24VDC BA
HW functional status	FS03
Firmware version	V0.0
• FW update possible	No
usable BaseUnits	BU type A0
Color code for module-specific color identification plate	CC01
Product function	
• I&M data	Yes; I&M0 to I&M3
Isochronous mode	No
Engineering with	
<ul> <li>STEP 7 TIA Portal configurable/integrated from version</li> </ul>	V14
<ul> <li>STEP 7 configurable/integrated from version</li> </ul>	V5.5 SP3 / -
<ul> <li>PROFIBUS from GSD version/GSD revision</li> </ul>	One GSD file each, Revision 3 and 5 and higher
<ul> <li>PROFINET from GSD version/GSD revision</li> </ul>	GSDML V2.3
Operating mode	
• DI	Yes
Counter	No
Oversampling	No
• MSI	No
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	70 mA; All channels are supplied from the encoder supply
Encoder supply	
Number of outputs	8
Output voltage, min.	19.2 V
Short-circuit protection	Yes; per module
24 V encoder supply	
• 24 V	Yes
Short-circuit protection	Yes
<ul> <li>Output current per channel, max.</li> </ul>	700 mA
Output current per module, max.	700 mA
Power loss	
Power loss, typ.	1.6 W; 24 V, 8 inputs supplied via encoder supply
Address area	
Address space per module	

• Inputs	1 byte
Inputs     Hardware configuration	
	Van
Automatic encoding	Yes
Mechanical coding element	Yes
Type of mechanical coding element	Туре А
Selection of BaseUnit for connection variants	PU tare 40
<ul> <li>1-wire connection</li> <li>2-wire connection</li> </ul>	BU type A0 BU type A0
3-wire connection	
4-wire connection	BU type A0 with AUX terminals BU type A0 + Potential distributor module
Digital inputs	Bo type Ao + Potential distributor module
	8
Number of digital inputs	o Yes
Digital inputs, parameterizable	
Source/sink input	P-reading Yes
Input characteristic curve in accordance with IEC 61131, type 1 Input characteristic curve in accordance with IEC 61131, type 2	Yes
Input characteristic curve in accordance with IEC 61131, type 3	Yes
Input voltage	
Rated value (DC)	24 V
• for signal "0"	-30 to +5 V
• for signal "1"	+11 to +30V
Input current	
• for signal "1", typ.	6.8 mA
Input delay (for rated value of input voltage)	
for standard inputs	
— parameterizable	Yes; 0.05 / 0.1 / 0.4 / 0.8 / 1.6 / 3.2 / 12.8 / 20 ms (in each case + delay of 30 to
	500 $\mu$ s, depending on line length)
— at "0" to "1", min.	0.05 ms
— at "0" to "1", max.	20 ms
— at "1" to "0", min.	0.05 ms
— at "1" to "0", max.	20 ms
Cable length	
<ul> <li>shielded, max.</li> </ul>	1 000 m
<ul> <li>unshielded, max.</li> </ul>	600 m
Encoder	
Connectable encoders	
• 2-wire sensor	Yes
<ul> <li>— permissible quiescent current (2-wire sensor), max.</li> </ul>	2 mA
Interrupts/diagnostics/status information	
Diagnostics function	Yes
Alarms	
Diagnostic alarm	Yes
Diagnoses	
<ul> <li>Diagnostic information readable</li> </ul>	Yes
<ul> <li>Monitoring the supply voltage</li> </ul>	Yes
	Yes
— parameterizable	
Monitoring of encoder power supply	No
<ul><li>Monitoring of encoder power supply</li><li>Wire-break</li></ul>	No No
<ul><li>Monitoring of encoder power supply</li><li>Wire-break</li><li>Short-circuit</li></ul>	No No No
<ul> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> <li>Short-circuit</li> <li>Group error</li> </ul>	No No
<ul> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> <li>Short-circuit</li> <li>Group error</li> <li>Diagnostics indication LED</li> </ul>	No No Yes
Monitoring of encoder power supply     Wire-break     Short-circuit     Group error Diagnostics indication LED     Monitoring of the supply voltage (PWR-LED)	No No No Yes Yes; green PWR LED
<ul> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> <li>Short-circuit</li> <li>Group error</li> <li>Diagnostics indication LED</li> <li>Monitoring of the supply voltage (PWR-LED)</li> <li>Channel status display</li> </ul>	No No No Yes Yes; green PWR LED Yes; green LED
<ul> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> <li>Short-circuit</li> <li>Group error</li> <li>Diagnostics indication LED</li> <li>Monitoring of the supply voltage (PWR-LED)</li> <li>Channel status display</li> <li>for channel diagnostics</li> </ul>	No No No Yes Yes; green PWR LED Yes; green LED No
<ul> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> <li>Short-circuit</li> <li>Group error</li> <li>Diagnostics indication LED</li> <li>Monitoring of the supply voltage (PWR-LED)</li> <li>Channel status display</li> <li>for channel diagnostics</li> <li>for module diagnostics</li> </ul>	No No No Yes Yes; green PWR LED Yes; green LED
<ul> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> <li>Short-circuit</li> <li>Group error</li> <li>Diagnostics indication LED</li> <li>Monitoring of the supply voltage (PWR-LED)</li> <li>Channel status display</li> <li>for channel diagnostics</li> <li>for module diagnostics</li> </ul> Potential separation	No No No Yes Yes; green PWR LED Yes; green LED No
<ul> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> <li>Short-circuit</li> <li>Group error</li> <li>Diagnostics indication LED</li> <li>Monitoring of the supply voltage (PWR-LED)</li> <li>Channel status display</li> <li>for channel diagnostics</li> <li>for module diagnostics</li> <li>for module diagnostics</li> <li>Potential separation</li> </ul>	No No No Yes Yes; green PWR LED Yes; green LED No Yes; green/red DIAG LED
<ul> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> <li>Short-circuit</li> <li>Group error</li> <li>Diagnostics indication LED</li> <li>Monitoring of the supply voltage (PWR-LED)</li> <li>Channel status display</li> <li>for channel diagnostics</li> <li>for module diagnostics</li> <li>for module diagnostics</li> <li>Potential separation</li> <li>Potential separation channels</li> <li>between the channels</li> </ul>	No No Yes Yes; green PWR LED Yes; green LED No Yes; green/red DIAG LED
<ul> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> <li>Short-circuit</li> <li>Group error</li> <li>Diagnostics indication LED</li> <li>Monitoring of the supply voltage (PWR-LED)</li> <li>Channel status display</li> <li>for channel diagnostics</li> <li>for module diagnostics</li> <li>for module diagnostics</li> <li>Potential separation</li> <li>Potential separation channels</li> <li>between the channels</li> <li>between the channels and backplane bus</li> </ul>	No No Yes Yes; green PWR LED Yes; green LED No Yes; green/red DIAG LED
<ul> <li>Monitoring of encoder power supply</li> <li>Wire-break</li> <li>Short-circuit</li> <li>Group error</li> <li>Diagnostics indication LED</li> <li>Monitoring of the supply voltage (PWR-LED)</li> <li>Channel status display</li> <li>for channel diagnostics</li> <li>for module diagnostics</li> <li>for module diagnostics</li> <li>Potential separation</li> <li>Potential separation channels</li> <li>between the channels</li> </ul>	No No Yes Yes; green PWR LED Yes; green LED No Yes; green/red DIAG LED

Isolation	
Isolation tested with	707 V DC (type test)
Standards, approvals, certificates	
Suitable for safety functions	No
Ambient conditions	
Ambient temperature during operation	
<ul> <li>horizontal installation, min.</li> </ul>	-30 °C; < 0 °C as of FS03
<ul> <li>horizontal installation, max.</li> </ul>	60 °C
<ul> <li>vertical installation, min.</li> </ul>	-30 °C; < 0 °C as of FS03
<ul> <li>vertical installation, max.</li> </ul>	50 °C
Altitude during operation relating to sea level	
<ul> <li>Installation altitude above sea level, max.</li> </ul>	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	
Width	15 mm
Height	73 mm
Depth	58 mm
Weights	
Weight, approx.	28 g

last modified:

8/16/2023 🖸