## SIEMENS

## Data sheet

## 6ES7134-6GD01-2BA1



SIMATIC ET 200SP, ANALOG INPUT MODULE, AI 4XI 2-/4-WIRE STANDARD, PACKING UNIT: 10 PIECES, FITS TO BU-TYPE A0, A1, COLOR CODE CC03, MODULE DIAGNOSIS, 16BIT, +/-0,3%

General information	
Product type designation	AI 4xI 2-/4-wire ST
HW functional status	From FS02
Firmware version	
• FW update possible	Yes
usable BaseUnits	BU type A0, A1
Color code for module-specific color identification plate	CC03
Product function	
• I&M data	Yes; I&M0 to I&M3
Isochronous mode	No
<ul> <li>Measuring range scalable</li> </ul>	No
Engineering with	
STEP 7 TIA Portal configurable/integrated from version	V14 / -
<ul> <li>STEP 7 configurable/integrated from version</li> </ul>	V5.6 and higher
<ul> <li>PCS 7 configurable/integrated from version</li> </ul>	V8.1 SP1
<ul> <li>PROFIBUS from GSD version/GSD revision</li> </ul>	One GSD file each, Revision 3 and 5 and higher
<ul> <li>PROFINET from GSD version/GSD revision</li> </ul>	GSDML V2.3
Operating mode	
Oversampling	No
• MSI	No
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	No
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	37 mA; without sensor supply
Encoder supply	
24 V encoder supply	
• 24 V	Yes
Short-circuit protection	Yes
Output current, max.	20 mA; max. 50 mA per channel for a duration < 10 s
Power loss	
Power loss, typ.	0.85 W; Without encoder supply voltage
Address area	
Address space per module	
Address space per module, max.	8 byte; + 1 byte for QI information

Subject to change without notice © Copyright Siemens

Hardware configuration	
Automatic encoding	Yes
Mechanical coding element	Yes
Type of mechanical coding element	Туре А
Selection of BaseUnit for connection variants	
2-wire connection	BU type A0, A1
• 4-wire connection	BU type A0, A1
Analog inputs	
Number of analog inputs	4; Differential inputs
permissible input current for current input (destruction limit), max.	50 mA
Cycle time (all channels), min.	Sum of the basic conversion times and additional processing times (depending on the parameterization of the active channels)
Input ranges (rated values), currents	
• 0 to 20 mA	Yes; 16 bit incl. sign
— Input resistance (0 to 20 mA)	100 $\Omega$ ; + approx. 0.7 V diode forward voltage in 2-wire operation
• -20 mA to +20 mA	Yes
<ul> <li>Input resistance (-20 mA to +20 mA)</li> </ul>	100 Ω
• 4 mA to 20 mA	Yes; 15 bit
— Input resistance (4 mA to 20 mA)	100 $\Omega$ ; + approx. 0.7 V diode forward voltage in 2-wire operation
Cable length	
shielded, max.	1 000 m
Analog value generation for the inputs	
Measurement principle	integrating (Sigma-Delta)
Integration and conversion time/resolution per channel	
<ul> <li>Resolution with overrange (bit including sign), max.</li> </ul>	16 bit
Integration time, parameterizable	Yes
<ul> <li>Interference voltage suppression for interference frequency f1 in Hz</li> </ul>	16.6 / 50 / 60 Hz
Conversion time (per channel)	180 / 60 / 50 ms
Smoothing of measured values	
<ul> <li>Number of smoothing levels</li> </ul>	4; None; 4/8/16 times
<ul><li>Number of smoothing levels</li><li>parameterizable</li></ul>	4; None; 4/8/16 times Yes
-	
parameterizable	
• parameterizable Encoder	
parameterizable Encoder Connection of signal encoders	Yes
parameterizable Encoder Connection of signal encoders     o for voltage measurement	Yes No
parameterizable Encoder Connection of signal encoders     ofor voltage measurement     ofor current measurement as 2-wire transducer	Yes No Yes
parameterizable Encoder Connection of signal encoders     ofor voltage measurement     for current measurement as 2-wire transducer     — Burden of 2-wire transmitter, max.	Yes No Yes 650 Ω
<ul> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>— Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul>	Yes No Yes 650 Ω
parameterizable  Encoder  Connection of signal encoders      ofor voltage measurement     ofor current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.     ofor current measurement as 4-wire transducer  Errors/accuracies	Yes No Yes 650 Ω Yes
parameterizable  Encoder  Connection of signal encoders      for voltage measurement     for current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.     for current measurement as 4-wire transducer  Errors/accuracies Linearity error (relative to input range), (+/-)	Yes No Yes 650 Ω Yes 0.01 %
parameterizable  Encoder  Connection of signal encoders      ofor voltage measurement     ofor current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.     ofor current measurement as 4-wire transducer  Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-)	Yes No Yes 650 Ω Yes 0.01 % 0.005 %/K
parameterizable  Encoder  Connection of signal encoders      ofor voltage measurement      ofor current measurement as 2-wire transducer      — Burden of 2-wire transmitter, max.      ofor current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input	Yes No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels
<ul> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Current, relative to input range, (+/-)</li> </ul>	Yes No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels
<ul> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer <ul> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies <ul> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> </ul> </li> </ul>	Yes No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 %
<ul> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer <ul> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies <ul> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range <ul> <li>Current, relative to input range, (+/-)</li> </ul> </li> </ul></li></ul>	Yes No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.05 %
<ul> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer <ul> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Current, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Current, relative to input range, (+/-)</li> </ul>	Yes No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 %
<ul> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer <ul> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Current, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Current, relative to input range, (+/-)</li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference &lt; rated value of input range), min.</li> </ul>	Yes No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 %
<ul> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer <ul> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies <ul> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> </ul> </li> <li>Operational error limit in overall temperature range <ul> <li>Current, relative to input range, (+/-)</li> </ul> </li> <li>Basic error limit (operational limit at 25 °C) <ul> <li>Current, relative to input range, (+/-)</li> </ul> </li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference &lt; rated value of input range), min.</li> <li>Common mode voltage, max.</li> </ul>	Yes No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 % 0.3 % erence frequency 70 dB 10 V
<ul> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer <ul> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies <ul> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Current, relative to input range, (+/-)</li> </ul> </li> <li>Basic error limit (operational limit at 25 °C) <ul> <li>Current, relative to input range, (+/-)</li> </ul> </li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference &lt; rated value of input range), min.</li> <li>Common mode voltage, max.</li> <li>Common mode interference, min.</li> </ul>	Yes No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 %
<ul> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer <ul> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Current, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Current, relative to input range, (+/-)</li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference &lt; rated value of input range), min.</li> <li>Common mode voltage, max.</li> <li>Common mode interference, min.</li> </ul>	Yes No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 % 0.3 % erence frequency 70 dB 10 V 90 dB
<ul> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer <ul> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Current, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Current, relative to input range, (+/-)</li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference</li> <li>Series mode interference (peak value of interference &lt; rated value of input range), min.</li> <li>Common mode voltage, max.</li> <li>Common mode interference, min.</li> </ul>	Yes No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 % 0.3 % erence frequency 70 dB 10 V
<ul> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer <ul> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies <ul> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> </ul> </li> <li>Operational error limit in overall temperature range <ul> <li>Current, relative to input range, (+/-)</li> </ul> </li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Current, relative to input range, (+/-)</li> </ul> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference</li> <li>Series mode interference (peak value of interference &lt; rated value of input range), min.</li> <li>Common mode voltage, max.</li> <li>Common mode interference, min.</li> <li>Interrupts/diagnostics/status information <ul> <li>Diagnostics function</li> <li>Alarms</li> </ul></li>	Yes No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 % 0.3 % erence frequency 70 dB 10 V 90 dB
<ul> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer <ul> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies <ul> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> </ul> </li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range <ul> <li>Current, relative to input range, (+/-)</li> </ul> </li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Current, relative to input range, (+/-)</li> </ul> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference &lt; rated value of input range), min.</li> <li>Common mode interference, min.</li> Interrupts/diagnostics/status information Diagnostics function <ul> <li>Alarms</li> <li>Diagnostic alarm</li> </ul>	Yes No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 % 0.3 % rence frequency 70 dB 10 V 90 dB
<ul> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders <ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies <ul> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> </ul> </li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Current, relative to input range, (+/-)</li> </ul> <li>Basic error limit (operational limit at 25 °C) <ul> <li>Current, relative to input range, (+/-)</li> </ul> </li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference &lt; rated value of input range), min.</li> <li>Common mode interference (peak value of interference &lt; rated value of input range), min.</li> <li>Common mode interference, min.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostic sfunction</li> <li>Alarms <ul> <li>Limit value alarm</li> </ul> </li>	Yes No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 % 0.3 % erence frequency 70 dB 10 V 90 dB
<ul> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders <ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies <ul> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> </ul> </li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Current, relative to input range, (+/-)</li> </ul> <li>Basic error limit (operational limit at 25 °C) <ul> <li>Current, relative to input range, (+/-)</li> </ul> </li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference value of input range), min.</li> <li>Common mode interference (peak value of interference &lt; rated value of input range), min.</li> <li>Common mode interference, min.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostic alarm <ul> <li>Limit value alarm</li> <li>Diagnoses</li> </ul> </li>	Yes No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 % 0.3 % erence frequency 70 dB 10 V 90 dB
<ul> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders <ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies <ul> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> </ul> </li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Current, relative to input range, (+/-)</li> </ul> <li>Basic error limit (operational limit at 25 °C) <ul> <li>Current, relative to input range, (+/-)</li> </ul> </li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference &lt; rated value of input range), min.</li> <li>Common mode interference (peak value of interference &lt; rated value of input range), min.</li> <li>Common mode interference, min.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostic sfunction</li> <li>Alarms <ul> <li>Limit value alarm</li> </ul> </li>	Yes No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.3 % 0.3 % erence frequency 70 dB 10 V 90 dB

Short-circuit	Yes; 2-wire mode: Short-circuit of the encoder supply to ground or of an input to
	the encoder supply Yes
Group error	
Overflow/underflow	Yes
Diagnostics indication LED	
Monitoring of the supply voltage (PWR-LED)	Yes; green LED
Channel status display	Yes; green LED
<ul> <li>for channel diagnostics</li> </ul>	No
for module diagnostics	Yes; green/red LED
Potential separation	
Potential separation channels	
between the channels	Yes; channel group-specific between 2-wire current input group and 4-wire voltage input group
<ul> <li>between the channels and backplane bus</li> </ul>	Yes
<ul> <li>between the channels and the power supply of the electronics</li> </ul>	Yes; only for 4-wire transducer
Permissible potential difference	
between the inputs (UCM)	10 V DC
Isolation	
Isolation tested with	707 V DC (type test)
Ambient conditions	
Ambient temperature during operation	
<ul> <li>horizontal installation, min.</li> </ul>	-30 °C; < 0 °C as of FS02
<ul> <li>horizontal installation, max.</li> </ul>	60 °C
<ul> <li>vertical installation, min.</li> </ul>	-30 °C; < 0 °C as of FS02
<ul> <li>vertical installation, max.</li> </ul>	50 °C
Altitude during operation relating to sea level	
<ul> <li>Installation altitude above sea level, max.</li> </ul>	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	
Width	15 mm
Height	73 mm
Depth	58 mm
Weights	
Weight, approx.	31 g
last modified:	9/7/2023 🖸