



KBR 18L

Split-core current transformer



Round conductor 18,4 mm
 Transformer width 49,0 mm
 Height 80,1 mm
 Depth 59 mm



Primary current [A]	Burden [VA]	Secondary current [A] / Class			
		5 A Cl. 1 Art.-no.	5 A Cl. 0,5 Art.-no.	1 A Cl. 1 Art.-no.	1 A Cl. 0,5 Art.-no.
100	0,3			18L-0001	
125	0,5			18L-0002	
150	1	18L-5001		18L-0003	
200	0,2				18L-0004
	1,5	18L-5002		18L-0005	
250	0,5				18L-0006
	1		18L-5003		
	2	18L-5004			
	2,5			18L-0007	

	Art.-no.
	Snap-on mounting, type I 55017

- Split-core current transformers are mainly used for an easy fitment and subsequent assembly into an already existing installation, without separating the primary conductor.
- The compact split-core current transformer KBR 18L has been developed to have easy access in already existing installations.
- Due to the „click“-system and the fixing-clasps even a one-hand mounting is possible.
- The KBR 18L with secondary 1A will be delivered with 2.5 m connection cable 2 x 0.5 mm² (color coded; S1 = brown; S2 = blue). Other lengths of the connection cables are possible on request.
 The secondary 5A – version will be delivered with 0.5m connection cable 2 x 1.5 mm².
- Operating temperature: -5°C < T < +50°C
- Storage temperature: -25°C < T < +70°C