

L7SA Serial Type

Rated Speed (rpm)	Maximum Speed (rpm)	Flange Size	Applicable Motor	Applicable Drive	Standard Encoder Type	Encoder Cable		Power Cable						
					Serial Type	Serial	Abs	For power	Power + Brake	Brake				
3,000	5,000	□40	FALR5A	L7SA001B	* 18Bit Serial M-Turn Absolute	APCS-E □ □ □ ES	APCS-E □ □ □ ES1	APCS-P □ □ □ LS	-	APCS-B □ □ □ QS				
		□40	FAL01A	L7SA001B										
		□40	FAL015A	L7SA004B										
		□60	FBL01A	L7SA001B										
		□60	FBL02A	L7SA002B										
		□60	FBL04A	L7SA004B										
		□80	FCL04A	L7SA004B										
		□80	FCL06A	L7SA008B										
		□80	FCL08A	L7SA008B										
		□80	FCL10A	L7SA010B										
		□60	FB01A	L7SA001B										
		□60	FB02A	L7SA002B										
		□60	FB04A	L7SA004B										
		□80	FC04A	L7SA004B										
		□80	FC06A	L7SA008B										
		□80	FC08A	L7SA008B										
		□80	FC10A	L7SA010B										
		□130	FE09A	L7SA010B										
		□130	FE15A	L7SA020B										
		□130	FE22A	L7SA020B										
□130	FE30A	L7SA035B												
□180	FF30A	L7SA035B												
□180	FF50A	L7SA050B												
2,000	3,000	□80	FCL03D	L7SA004B	* 19Bit Serial M-Turn Absolute	APCS-E □ □ □ ES	APCS-E □ □ □ ES1	APCS-P □ □ □ LS	-	APCS-B □ □ □ QS				
		□80	FCL05D	L7SA008B										
		□80	FCL06D	L7SA008B										
		□80	FCL07D	L7SA008B										
		□80	FC03D	L7SA004B										
		□80	FC05D	L7SA008B										
		□80	FC06D	L7SA008B										
		□80	FC07D	L7SA008B										
		□130	FE06D	L7SA008B										
		□130	FE11D	L7SA010B										
	□130	FE16D	L7SA020B											
	□130	FE22D	L7SA020B											
	□180	FF22D	L7SA020B											
	□180	FF35D	L7SA035B											
	□180	FF55D	L7SA050B											
	□220	FG22D	L7SA020B											
	2,700	□220	FG35D	L7SA035B										
	3,000	□220	FG55D	L7SA050B										
	1,500	3,000	□130	FE05G				L7SA008B	APCS-E □ □ □ DS	APCS-E □ □ □ DS1	APCS-P □ □ □ HS	APCS-P □ □ □ NB	-	
			□130	FE09G				L7SA010B						
□130			FE13G	L7SA020B										
□130			FE17G	L7SA020B										
□180			FF20G	L7SA020B										
2,700		□180	FF30G	L7SA035B										
3,000		□180	FF44G	L7SA050B										
		□220	FG20G	L7SA020B										
		2,700	□220	FG30G	L7SA035B									
		3,000	□220	FG44G	L7SA050B									
	□220		FG20M	L7SA020B										
1,000	2,000	□130	FE03M	L7SA004B	APCS-P □ □ □ HS	APCS-P □ □ □ NB	-							
		□130	FE06M	L7SA008B										
		□130	FE09M	L7SA010B										
		□130	FE12M	L7SA020B										
		□180	FF12M	L7SA020B										
	1,700	□180	FF20M	L7SA020B										
		2,000	□180	FF30M			L7SA035B							
			□180	FF44M			L7SA050B							
		2,000	□220	FG12M			L7SA020B							
			□220	FG20M			L7SA020B							
1,700	□220	FG30M	L7SA035B											
2,000	□220	FG44M	L7SA050B											